

Low-Voltage Fuse Systems


DIAZED Fuse Systems

DIAZED fuse links


Dimensional drawings

500 V DC


5SA1, 5SA2




5SB1, 5SB2



5SB3, 5SB4




5SC1, 5SC2



690 V AC/600 V DC and 750 V AC/750 V DC

5SD8, 5SD6



Fuse link	TNDz/E16, NDz/E16						
Rated current A	2	4	6	10	16	20	25
Dimension d	6	6	6	8	10	12	14

Fuse link	DII/E27						
Rated current A	2	4	6	10	16	20	25
Dimension d	6	6	6	8	10	12	14

Fuse link	DIII/E33						
Rated current A	32	35	50	63			
Dimension d	16	16	18	20			

Fuse link	DIV/R1¼"						
Rated current A	80	100					
Dimension d	5	7					

Fuse link	DIII/E33									
Rated current A	2	4	6	10	16	20	25	35	50	63
Dimension d	6	6	6	8	10	12	14	16	18	20